8EXF300.0000-00

1 Order data

Model number	Short description	Figure
	Fan modules	
8EXF300.0000-00	ACOPOS P3 ELKO fan module, replacement fan for ACOPOS P3 servo drive double-width (8EI017xxD/8EI022xxD/8EI024/8EI034/8EI044)	

Table 1: 8EXF300.0000-00 - Order data

2 Technical data

Model number	8EXF300.0000-00
General information	
Short description	ACOPOS P3 ELKO fan module, replacement fan for ACOPOS P3 servo drive double-width (8EI017xxD/8EI022xxD/8EI024/8EI034/8EI044)
Certifications	
CE	Yes
UL	cULus E225616 Power conversion equipment
Mechanical properties	
Dimensions	
Width	65 mm
Height	62 mm
Depth	33 mm
Weight	40 g

Table 2: 8EXF300.0000-00 - Technical data

3 Replacing fan module 8EXF300.0000-00

Fan module 8EXF300.0000-00 is installed on the bottom of the ACOPOS P3 8EI servo drive.



Figure 1: Fan module 8EXF300.0000-00

Procedure

1. Disconnect the ACOPOS P3 drive system from the power system and secure it against being switched on again.

   > **Danger!**
   >
   > **Before starting work, disconnect the power supply and wait 5 minutes to ensure that the DC bus of the ACOPOS P3 drive system has discharged. Observe regulations!**

2. The fan module is snapped into the ACOPOS P3 module with a snap-fit connector (❶).




Figure 2: Removing the fan module

Carefully push the fan module outwards (❶) using the side tab and pull it out of the ACOPOS P3 module in the direction of the arrow (❷).

3. Slide the new fan module into the ACOPOS P3 module and push it downwards in the direction of the arrow until the snap-fit connector audibly engages.



Figure 3: Installing the fan module

Information:

8EXF300.0000-00 fan modules have an average service life of approx. 65,000 h.

B&R recommends replacing all fan modules on an ACOPOS P3 module at the same time.