X20(c)BB82

1 General information

1.1 Other applicable documents

For additional and supplementary information, see the following documents.

Other applicable documents

Document name	Title
MAX20	X20 System user's manual
MAEMV	Installation / EMC guide

1.2 Coated modules

Coated modules are X20 modules with a protective coating for the electronics component. This coating protects X20c modules from condensation and corrosive gases.

The modules' electronics are fully compatible with the corresponding X20 modules.

For simplification purposes, only images and module IDs of uncoated modules are used in this data sheet.

The coating has been certified according to the following standards:

- Condensation: BMW GS 95011-4, 2x 1 cycle
- · Corrosive gas: EN 60068-2-60, method 4, exposure 21 days



1.2.1 Starting temperature

The starting temperature describes the minimum permissible ambient temperature in a voltage-free state at the time the coated module is switched on. This is permitted to be as low as -40°C. During operation, the conditions as specified in the technical data continue to apply.

Information:

It is important to absolutely ensure that there is no forced cooling by air currents in the closed control cabinet, e.g. due to the use of a fan or ventilation slots.

1.3 Order data

Order number	Short description	Figure
	System modules for expandable bus controllers	
X20BB82	X20 bus base, for X20 base module (BC, HB, etc.) and X20 power supply module, with 2 expansion slots for 2 X20 add- on modules (IF, HB, etc.), X20 end cover plates (left and right) X20AC0SL1/X20AC0SR1 included	
X20cBB82	X20 bus base, coated, for X20 base module (BC, HB, etc.) and X20 power supply module, with 2 expansion slots for 2 X20 add- on modules (IF, HB, etc.), X20 end cover plates (left and right) X20AC0SL1/X20AC0SR1 included	S S S

Table 1: X20BB82, X20cBB82 - Order data

X20(c)BB82

1.4 Module description

The bus module has 2 expansion slots. The following modules are used on this module:

- Base module (BC, HB, etc.)
- Two add-on modules (IF, HB, etc.)
- Supply module

The left and right end cover plates are included in delivery.

• Bus base with 2 expansion slots

Information:

The bus controller must be placed in the rightmost slot.

2 Technical description

2.1 Technical data

Order number	X20BB82	X20cBB82	
Short description			
Bus module	Bus base with 2	expansion slots	
General information			
Power consumption			
Bus	0.70 W		
Internal I/O	-		
Additional power dissipation caused by actuators	-		
(resistive) [W]			
Certifications			
CE	Yes		
UKCA	Yes		
ATEX	Zone 2, II 3G Ex nA nC IIA T5 Gc IP20, Ta (see X20 user's manual) FTZÚ 09 ATEX 0083X		
UL	cULus E115267 Industrial control equipment		
HazLoc	cCSAus 244665 Process control equipment for hazardous locations Class I, Division 2, Groups ABCD, T5		
DNV	Temperature: B (0 to 55°C) Humidity: B (up to 100%) Vibration: B (4 g) EMC: B (bridge and open deck)		
LR	ENV1		
KR	Yes		
ABS	Yes		
BV	EC33B Temperature: 5 - 55°C Vibration: 4 g EMC: Bridge and open deck		
EAC	Yes		
KC	Yes	-	
I/O power supply			
Nominal voltage	24 V	DC	
Permissible contact load	10	A	
Operating conditions			
Mounting orientation			
Horizontal	Yes		
Vertical	Ye	S	
Installation elevation above sea level			
0 to 2000 m	No limitation		
>2000 m	Reduction of ambient temperature by 0.5°C per 100 m		
Degree of protection per EN 60529	IP20		
Ambient conditions			
Temperature			
Operation			
Horizontal mounting orientation	-25 to		
Vertical mounting orientation	-25 to 50°C		
Derating	-		
Starting temperature	-	Yes, -40°C	
Storage	-40 to		
Transport	-40 to 85°C		
Relative humidity			
Operation	5 to 95%, non-condensing	Up to 100%, condensing	
Storage	5 to 95%, non-condensing		
Transport	5 to 95%, non	-condensing	
Mechanical properties			
Note	Left and right X20 end cover plates included in delivery		
Pitch	87.5 ^{+0.2} mm		

Table 2: X20BB82, X20cBB82 - Technical data

2.2 Voltage routing

• •	
• •	
• •	
• •	
• •	
• •	
•	+24 VDC
•	GND