8GF60-110 premium

Technical data

18	

	8GF60-110hh004kln	8GF60-110hh005kln	8GF60-110hh008kin	8GF60-110hh010kin	8GF60-110hh016kIn	8GF60-110hh020kin	8GF60-110hh025kin	8GF60-110hh032kin	8GF60-110hh040kin	8GF60-110hh050kin	8GF60-110hh064kin	8GF60-110hh100kln
Gearbox												
Number of gear stages	1	1	1	1	2	2	2	2	2	2	2	2
Gear ratio i	4	5	8	10	16	20	25	32	40	50	64	100
Nominal output torque T _{2N} [Nm]	300	260	150	125	300	300	260	300	260	260	150	125
Max. output torque T _{2max} [Nm]	480	416	240	200	480	480	416	480	416	416	240	200
E-stop torque T _{2stop} [Nm]	650	650	380	480	650	650	650	650	650	650	380	480
Idle torque [Nm] at 20°C and 3000 rpm	3.65	2.6	1.4	1.15	0.95	0.7	0.6	0.45	0.4	0.35	0.35	0.3
Max. average drive speed $n_{1N50\%}$ [rpm] at 50% T_{2N} and S1	1300	1650	2650	3150	3150	3750	4000	4000	4000	4000	4000	4000
Max. average drive speed $n_{1N100\%}$ [rpm] at 100% T_{2N} and S1	1000	1300	2250	2750	2350	2800	3450	4000	4000	4000	4000	4000
Max. drive speed n _{1max} [rpm]						85	500					
Max. backlash J _t [arcmin]	3	3	3	3	5	5	5	5	5	5	5	5
Reduced backlash J _t [arcmin] less than							1					
Torsional rigidity C _{t21} [Nm/arcmin]	90	90	90	90	80	80	80	80	80	80	80	80
Tilting rigidity C _{2K} [Nm/arcmin]						5	90					
Max. breakdown torque M _{2Kmax} [Nm]						5	34					
Max. radial force Fr _{max} [N] for 30,000 h						48	300					
Max. radial force Fr _{max} [N] for 20,000 h						55	500					
Max. axial force Fa _{max} [N] for 30,000 h						84	100					
Max. axial force Fa _{max} [N] for 20,000 h						95	500					
Operating noise L _{PA} [dB(A)]						(68					
Efficiency at full load ŋ [%]	98	98	98	98	95	95	95	95	95	95	95	95
Min. operating temperature B _{Tempmin} [°C]						-:	25					
Max. operating temperature B _{Tempmax} [°C]						(90					
Mounting orientation						А	ıny					
Protection						IF	P65					
Weight m [kg]	6.5	6.5	6.5	6.5	8	8	8	8	8	8	8	8
Moment of inertia J ₁ [kgcm ²]	2.94	2.51	2.08	2	1.73	1.65	1.3	1.6	1.24	0.8	0.85	0.75


NOTE – Output torque / Max. output torque: This refers to an output shaft speed of $n_2 = 100$ rpm and application factor $K_A = 1$ as well as S1 operating mode for electrical machines and $T = 30^{\circ}$ C, depending on the diameter of the motor shaft. The maximum output torque is only permissible for 30,000 revolutions!


NOTE – E-stop torque: Approved for 1000x

NOTE – Axial / radial force: With reference to the middle of the output shaft; the entries refer to an output shaft speed of n₂ = 100 rpm and application factor K_A = 1 as well as S1 operating mode for electrical machines and T =


NOTE – Running noise: Noise level at a distance of 1 m; at an output speed of $n_1 = 3000$ rpm without a load; i = 5 **NOTE – Operating temperature:** With reference to the middle of the housing surface **NOTE – Weight:** Planetary gearbox including universal flange (specific weight upon request)


1-stage gear





2-stage gear





Adapter flange - Overview of dimensions

The flange length L completes the diagram for determining the gearbox length.

8GF60-110	8LSA3	8LSA4	8LSA5	8LVA2	8LVA3	8JSA3	8JSA4	8JSA5	8JSA6	8LSN4	8LSN5	80MPH
One-stage												
Flange length L [mm]	43.4	43.4	53.4		43.4		43.4	53.4	64.5	43.4	53.4	43.4
Flange diameter Q [mm]	115	115	142		115		115	115	142	120	142	115
Two-stage												
Flange length L [mm]	38.8	48.8	58.9	38.8	48.8	38.8	48.8	58.9		48.8	58.9	48.8
Flange diameter Q [mm]	90	115	142	90	90	90	90	115		115	142	90